
# SPECIFICATION SHEET


V3.0





**OPTION 1 (STANDARD)** Flush Canopy

Remote power supply



Vertical wires Remote power supply No upcharge OPTION 3 Surface Canopy Integral power supply Upcharge applies

# COVENANT CAPSULE 1500

# DESCRIPTION

Informed by the interlocking components of a snake's spine, Covenant is Lost Profile's contemporary take on a traditional glass chandelier.

#### MATERIALS

Brass , glass & aluminium

#### DIMENSIONS

Length: 1513mm (59.6") Width: 765mm (30.1") Height: 144mm (5.7")

LAMPING LED strip WEIGHT 17kg (37.5lbs)

LED COLOUR TEMP Warm White 3000k 2700k Available upon request No upcharge

VOLTAGE/WATTAGE 12V DC @ 70W LUMENS/CRI 5250Im @ 90+ CRI\* \*From the source

DRIVER 12V 90W 0-10V DIMMABLE

STANDARD FINISHES Blonde Brass, Aged Brass, Dark Bronze (these finishes are waxed)

# CUSTOM SURFACE FINISHES

Brushed Nickel, Chrome plating (Add 20%) Clear enamel & powder coated finishes available on request (Add 10%)

# MAINTENANCE

All LOST PROFILE metal surfaces are waxed. These metal surfaces are designed to age and patinate. Wear gloves when handling to avoid hand prints.

# CEILING CANOPY

Option 1 - Standard: x1 Hexagonal Flush canopy (Remote) 400 x 200 x 6mm (15.7 x 7.9 x 0.2in).

- Option 2 Vertical Wires: x1 Flush canopy + x3 Cable glider mounts (Remote) Ø100 x 6mm (Ø3.9 x 0.2in).
- Option 3 Surface Canopy: x1 Round Surface canopy (Integral) Ø350 x 70mm (Ø13.8 x 2.8in). Upcharge applies.

COVENANT CAPSULE 1500 is supplied with 4 x 2000mm (78.8") suspension wires and 2000mm (78.8") of clear 2-core power cable.

Please advise us if you require longer suspension wires & power cable.

#### INSTALLATION

Assembly required upon installing COVENANT as the glass is supplied separately to the internal substrate ring.

Allow at least 1 hour for installing the glass onto the ring. See installation guide for details.

# DRIVERS & DIMMING

LOST PROFILE products are supplied with 0-10V dimmable LED drivers. PHASE & DALI Dimmable drivers are available for some regions, upon request. The location of the driver needs to be considered, whether in a ceiling cavity, in a wall cavity, or ideally in an accessible electrical cabinet.

# PRICING & LEAD TIMES

Please contact us or your nearest LOST PROFILE representative for current pricing and lead times.

